

GF8005

BeiDou/GPS Binary Multi-source time Server

The GB8005 time synchronization system device provides accurate synchronization time signals to various power system automation devices by using the second synchronization signal and time information message sent by Beidou navigation system and GPS (Global Positioning System) satellite.



Applications

1. Providing time synchronization signals for power network automation devices such as fault recorder, event recorder, microcomputer relay protection device, microcomputer measurement and control device, merging unit, intelligent terminal and various safety automatic devices, telecontrol and microcomputer monitoring system, dispatching control system, etc.
2. The standard clock used for frequency monitoring, means the system frequency error accumulation is compared on the schedule by the difference between the power frequency clock and the standard time.
3. The synchronous clock used for phase measurement, the B G8005 is used to synchronize the sampling pulse, and the synchronization error is very small, which can ensure the accuracy of phase measurement.
4. For fault location, especially for the development of dual-terminal traveling wave ranging principle of the device to create conditions.
5. For relay protection device test, inspection line longitudinal protection (high frequency phase difference protection device).

Features

1. GPS, BD, CDMA three signal sources can be equipped with three options and two. especially suitable for electric power, machine room, hospital, etc.
2. Software interface can be set in English and Chinese, time zone can be set, panel with keys, easy to operate.
3. All-weather signal coverage, independent two-star system each other to ensure a long continuous high-precision timing.
4. Multiple 32-bit high-speed microprocessors + large-scale integrated FPGA chips, parallel high-speed data processing and various codes, excellent performance.
5. High-precision punctuality frequency is derived from adaptive synchronization technology, closed-loop control punctuality technology to tame constant temperature crystal oscillator, to achieve long-time high-precision punctuality.
6. Automatic selection of clock source according to priority, when receiving and decoding external IRIG-B (DC) code, automatic delay compensation correction technology is used to improve timing accuracy.

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

7. Separate 10 M/100M network ports (each port has a separate MAC address), flexible configuration, can be used in different sub-nets or different physical isolation networks, using NTP/SNTP protocols to provide time synchronization services.
8. Having two PTP V2 high-precision timing ethernet interfaces while down-compatible with V1 protocols, telecom-level timing accuracy, support multicast and unicast transmission modes, and support the best master clock selection algorithm. (Optional)
9. Providing programmable pulse, can be set for PPS/PPM/PPH; to provide settable frequency output, can be set to 100 K/1M/2M/5M/10M output, flexible and convenient.
10. High performance, wide range switching power supply, AC-DC compatible input, convenient and reliable, stable operation.
11. All signal input and output interfaces are photoelectric isolation measures, safe and reliable.
12. 1U Frame structure , 19 inch standard chassis, easy installation and maintenance.

Parameters

Parameters

1. Output Signal

| Timing signal type | Interface Type | Timing accuracy | | Interface parameters | Number of interfaces |
|--------------------|----------------|-----------------|---------------|----------------------------|----------------------|
| | | Beidou-1 | GPS | | |
| Pulse | TTL level | -0.14 μ S | -0.06 μ S | 5V level | 1 channels |
| Frequency | TTL level | | | 5V level | 1 channels |
| IRIG-B Time Code | RS485 level | 0.12 μ S | 0.2 μ S | Differential balance level | 1 channels |
| Serial port | RS232 | 0.18mS | 0.18mS | DB9 interface | 2 channels |
| | RS485 | 0.18mS | 0.18mS | Phoenix terminal | 2 channels |
| Ethernet | NTP/SNTP | 10mS | 10mS | RJ45 interface | 2/4 channels |
| | PTP | 0.2 μ S | 0.2 μ S | RJ45 interface | 2 channels |

2. Input Signal

| Name of clock source | Technical parameters | Remarks |
|----------------------|---|----------|
| Beidou-1 | Receiver frequency :1561 MHz (B1 signal) | Built-in |
| | Acceptance sensitivity :-127.6 dBmW | |
| | Capture time :35 S < 10 S; hot start and cold start | |
| | Timing accuracy : \leq 100 ns (unidirectional), \leq 20 ns (bidirectional) | |
| GPS | Receiver frequency :1575.42 MHz (L1 signal) | Built-in |
| | Receiving sensitivity: capture \leq -160 dBW, tracking \leq -163 dBW | |
| | Capture time :200 S <25 S; hot start and cold start | |
| | Timing accuracy : \leq 100 ns (1pps versus UTC time) | |
| | Simultaneous tracking: no less than 4 satellites in cold start; no less than 1 satellite in hot start; up to 12 satellites can be tracked at the same time, parallel 12 channels. | |

| | | |
|-------------------------------|---|----------|
| IRIG-B Time Code | The IRIG-B code shall comply with the provisions of the IRIG Standard 200-04 and contain the year and time signal quality information (reference IEEE C37.118-2005), the time is standard Beijing time. | Built-in |
| | Adopt IRIG-B000 format. | |
| | An automatic time delay compensation correction technique is used to μ s the timing accuracy better than 1 μ s. | |
| PTP input | With E2E and P2P two modes of timing. | Built-in |
| | Support one-step, two-steps working mode. | |
| Core punctuality clock module | Adopt high precision constant temperature crystal frequency precision reaches 2 E-11 order of magnitude. | Built-in |
| | Self-service error ≤ 18 us/24H. | |

3.Others

| Name of parameter | Parameters |
|--------------------------|---|
| Environmental parameters | Working temperature :-20 to +70oC |
| | Storage temperature :-45 to +85oC |
| | Humidity :<95% |
| Power supply | Power supply :220 V \pm 20% or 110 V \pm 20%,47 Hz-63 Hz |
| | DC power supply :220 V \pm 20% or 110 V \pm 20% |
| | Power consumption ≤ 15 W |
| EMC grade | Grade IV specified in the GB/T 17626-2008 |
| Alarm signal | Relay air contact (250 V,5A); Loss of satellite signals, power alarms, etc. |
| Appearance Weight | Standard 19" Case, height is 3 U, back pluggable structure, weight is 5 KG. Up to 8 slots are free to select various functional interface cards. |

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://gfuve.nt-rt.ru/> || gfvf@nt-rt.ru