

GF311

Three Phase Multi-function Phase Meter

It can be applied to electric power dispatching center, relay protection department or relay protection in power plant. Its metric division class makes it suitable for petroleum, railways and the iron and steel industries also.

Features

1. Simultaneously measuring three-phase voltages, current, power, frequency, power factor, phase, etc
2. Display vector map for the use of user directly
3. The smallest current it can measure is 1 mA, 2 mA above can display vector diagram
4. Range switches automatically, software for be calibrated
5. Small volume, light weight and the operation is simple, convenient
6. Horizontal liquid crystal big screen TFT displays all electric parameters
7. DSP digital signal processing chip, wide measuring range, high accuracy, good stability
8. It can store data; data can be using computer software to upload for management



Parameters

Electrical parameters	
Accuracy class	0.5%
Power supply	AC 85-265V 50/60Hz or Li-battery 5000mAh
Communication Port	RS232
Warming-up time	< 5min
Power consumption	≤5VA
Voltage measurement	
U1, U2, U3 Range	0-480V
Resolution	0.001V
Accuracy	0.2%
Current measurement	
I1, I2, I3 Range	1mA-10A or 50mA-200A or 50mA-500A
Resolution	0.5mA
Accuracy	0.5%

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Electrical parameters - continued
Active power measurement

Active accuracy 0.5%

Reactive power measurement

Accuracy 1%

Phase measurement

Range 0°-359.9°

Resolution 0.001°

Accuracy 0.1°

Frequency measurement

Range 45-65Hz

Resolution 0.001Hz

Accuracy 0.01Hz

Power factor measurement

Range -1 to 0 to +1

Resolution 0.0001

Accuracy 0.01

Mechanical parameters

Dimensions (W×D×H) (mm) 245×162×60

 Weight (kg) 1 (mains)
 6.5 (appendix and box)

Environmental conditions

Working temperature -10°C to 55°C

Working humidity 15%-85%RHD

Storage temperature -25°C to 70°C

Storage humidity 5%-95%RHD

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93