

GF334

Three Phase Power Analyzer

It is suitable for power companies and technical supervision departments. Industrial, mining, petroleum and chemicals, home appliances and manufacturing enterprises are in the suitable fields.

Functions

1. Measuring energy consumption values - the precise timing measurements of electrical equipment for short-term energy consumption; energy resolution: milli-watts; time resolution: milli-second; they are difficult to available for common instrument of power. The functions are used by pumping, cranes, air conditioning and other equipment in a work cycle connected power consumption.
2. The value of the measurement process- it can be recorded and tested continuously voltage, current, active power, reactive power and other electrical parameter values and curves in a dynamic process and graphically display.
3. To measure the instantaneous values - including the exchange parameters: U, I, P, Q, PF, phase angle, frequency, harmonics, etc.
4. Measurement of harmonics - measurement / display voltage and current waveforms and harmonic bar graph.
5. Check Meter - real live load calibration of various single-phase, three-phase energy meters.
6. Vector analysis - based on the voltage, current, phase error of judgment wiring, display vector graphics.



Features

1. Ultra-compact design, handheld, small size, light weight
2. The usage of multi-channel power supply, AC power supply can also be rechargeable battery-powered machine
3. High accuracy instrument, good stability, and wide range of voltage monitoring 0-1200V, current 1mA - 20A
4. It can be divided into direct current clamp measurements and precision measurements
5. It can measure three-phase voltage, current, active power, reactive power, power factor, frequency, phase, etc
6. Showing the AC waveform, vector diagram and determining the three-phase three-wire connection errors
7. It can measure harmonic content from 2 to 64 and the harmonic analysis
8. The measured data can record, query and upload print
9. Instrument calibration by using software to facilitate the correction instrument variation

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Parameters

Items	Range	Effective resolution	Accuracy1	Accuracy2	Remarks
Voltage	0-1200V	0.001V	0.1%	0.05%	2 ranges
Current	0-20A	0.001A	0.1%	0.05%	3 ranges
Clamp-on	0.01-100A	0.01A	0.15%	0.15%	Option ⁽¹⁾
Frequency	45-65Hz	0.001Hz	0.01Hz	0.002Hz	5 bit display
Active power	0 to $\pm U_{max} \times I_{max}$	0.01W	0.5%	0.2%	5 bit display
Reactive power	0 to $\pm U_{max} \times I_{max}$	0.01Var	1%	0.5%	5 bit display
Apparent power	0 to $\pm U_{max} \times I_{max}$	0.01VA	1%	0.5%	5 bit display
Active energy			0.5%	0.2%	
Reactive energy			1%	0.5%	
Harmonic	2nd-64th		0.5%	0.2%	
Power factor	0 to ± 0.9999	0.0001	± 0.001	± 0.0005	5 bit display
Phase	0-359.999°	0.005°	$\pm 0.05^\circ$	$\pm 0.02^\circ$	6 bit display

(1) Clamp-on 500A,3000A,5000A is optional.

Electrical parameters

Power supply	One-phase power supply(85-265VAC/45-70Hz) Lithium battery, 5000mAh
Communication port	RS232
Energy constant	3600imp/kWh, 360000imp/kWhx4
Frequency Influence	≤ 20 ppm/Hz
Pulse Interface	TTL energyx6

Mechanical parameters

Main machine (L×W×H) (mm)	240×157×60
Weight (kg)	1.5
Carrier dimension (L×W×H) (mm)	470×380×220
Carrier weight (kg)	10.6 (Including three clamp-on (100A), wires and software)

Environmental conditions

Environment	-10 to +55°C, 15-85%RHD
Altitude (m)	-10 to 3500
Temperature	-20°C to 65°C
Temperature	≤ 25 ppm/°C (U/I), ≤ 50 ppm/°C (others)

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93