

GF333

Multi-function Standard Meter

GF333 can be used as a calibration device standard meter, also as a testing calibrator in measurement test center of grid corporation, power company and measurement department in power plant, national levels of measurement mechanism, quality inspection departments, research institutes, tertiary institutions, industrial and mining enterprises, electric energy meter and electrical instrument production enterprises etc.



Features

1. Measure the AC voltage, current, active power, reactive power, frequency, phase angle and power factor etc
2. Measure the AC voltage, current 2~31 harmonic content and waveform distortion degree
3. Measure active power energy error, reactive power energy error, the maximum output pulse frequency is to 2 MHz
4. Measure calibration device of voltage, current, power stability
5. Measure calibration device the standard deviation of estimate
6. Measure the voltage of the calibration device three-phase symmetric degrees, the current of three three-phase symmetric degree
7. Measure calibration device of the magnetic induction
8. Measure DC voltage and DC current
9. Transducer measurement
10. With RS232 interface, it can be controlled by PC operation
11. Core part uses the 32 bit DSP and 16 bit low power and high speed DAC consists of high accuracy AC collector
12. Using 6.5 inch TFT color LCD screen, character display clear chart. Have the advantages of wide measuring range, high precision, stable and reliable operation, simple operation etc

Parameters

Electrical parameters

Accuracy class	0.02%, 0.05%
Power supply	AC 220 V±10% or 110 V±10%, 50/60Hz
Power consumption	< 30VA
Warming-up time	< 30min

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Electrical parameters - continued
Voltage measurement

U1, U2,U3	6.25V, 12.5V, 25V, 50V, 100V, 200V, 400V, 800V (switch automatically), max 1000V
Range	(0 -120%) RG
Resolution	0.01% RG
Accuracy	0.02% RD or 0.05% RD

Current measurement

I1, I2, I3	0.25, 0.5, 1, 2.5, 5, 10, 25, 50, 100A(switch automatically)
Range	(0-120%) RG
Resolution	0.01% RG
Accuracy	0.02% RD or 0.05% RD

Power measurement

Active accuracy	0.02% RD or 0.05% RD
Reactive accuracy	0.05% RD or 0.1% RD
Apparent accuracy	0.02% RD or 0.05% RD

Energy measurement

Active accuracy	0.02% RD or 0.05% RD
Reactive accuracy	0.05% RD or 0.1% RD

Phase measurement

Range	0.00° -359.99°
Resolution	0.001°
Accuracy	0.02° (voltage \geq 50V and current \geq 250mA)

Frequency measurement

Range	45-65Hz
Resolution	0.001Hz
Accuracy	0.002Hz

Power factor measurement

Range	-1.0 ~ 0 ~ +1.0
Resolution	0.0001
Accuracy	0.0005

Electric energy pulse output

Pulse constant range	1-2880000000
Output frequency of max. pulse	600 kHz
Load capacity	> 2mA
Default pulse output frequency	10K Hz - 600 kHz

Energy pulse Input

Input range of pulse constant	600-700000
Setting range of test pulse	1-999999999

Electrical parameters - continued
Energy pulse Input - continued

Max. pulse receiving frequency	2MHz
Pulse input level	5V

Voltage/current harmonics measurement

Times	2-31
Error	0.05%
Distortion degree error	0.05%

Transducer measurement

DC voltage range	±1, ±5, ±10, ±20 V
Accuracy	0.01%
DC current range	±1, ±2.5, ±5, ±10, ±20mA
Accuracy	0.01%
Ripple error	1%

DC measurements (option)

DC voltage	50V, 100V, 200V, 400V, 800V (switch automatically), max 1
Range	(0 -120%) RG
Resolution	0.01% RG
Accuracy	0.02% RD
DC current	0.1A, 0.3A, 1A, 3A, 10A, 30 A (switch automatically)
Range	(0-120%) RG
Resolution	0.01% RG
Accuracy	0.02% RD

Mechanical parameters

Dimensions (W×H×D) (mm)	440×360×160
Weight (kg)	10

Environmental conditions

Operating temperature	10°C to 30°C
Relative humidity	≤ 85%

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93