

# GF333B

## Three Phase Reference Standard Meter

*GF333B is a portable reference standard meter used to test three phase meters and single phase meters, it designed to work both in the field and in the laboratory.*



### Features

1. High accuracy up to 0.05%
2. Wide testing range: voltage 5V-480V, current 1mA-120A
3. Testing type: 3 phase 4 wire, 3 phase 3 wire
4. Testing mode: active power, reactive power, apparent power
5. Harmonic analysis function
6. Waveform display function
7. Vector diagram function
8. Energy accumulating function
9. Internal pulse input port, testing meter's error directly



### Parameters

Electrical parameters	
Accuracy class	0.05%
Voltage supply	220V±10% or 110V±10%, 50/60Hz
Range	5V-480V
Error	±0.02% (50V-480V), ±0.05% (5V-50V)
Display range	5.000000V-480.0000V
Harmonic	2nd-63st
Range	1mA-120A
Error	±0.02% (0.2A-120A), ±0.05% (1mA-0.2A)
Display range	1.000000mA-120.0000A
Active power	±0.02% (0.2A-120A) ±0.05% (0.01A-0.2A) ±0.1% (0.001A-0.01A)
Reactive power	±0.05% (0.2A-120A), ±0.1% (0.001A-0.2A)
Apparent power	±0.05% (0.2A-120A), ±0.1% (0.001A-0.2A)
Active energy	±0.02% (0.2A-120A) ±0.05% (0.01A-0.2A) ±0.1% (0.001A-0.01A)

Архангельск (8182)63-90-72  
 Астана (7172)727-132  
 Астрахань (8512)99-46-04  
 Барнаул (3852)73-04-60  
 Белгород (4722)40-23-64  
 Брянск (4832)59-03-52  
 Владивосток (423)249-28-31  
 Волгоград (844)278-03-48  
 Вологда (8172)26-41-59  
 Воронеж (473)204-51-73  
 Екатеринбург (343)384-55-89  
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58  
 Иркутск (395)279-98-46  
 Казань (843)206-01-48  
 Калининград (4012)72-03-81  
 Калуга (4842)92-23-67  
 Кемерово (3842)65-04-62  
 Киров (8332)68-02-04  
 Краснодар (861)203-40-90  
 Красноярск (391)204-63-61  
 Курск (4712)77-13-04  
 Липецк (4742)52-20-81  
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13  
 Москва (495)268-04-70  
 Мурманск (8152)59-64-93  
 Набережные Челны (8552)20-53-41  
 Нижний Новгород (831)429-08-12  
 Новокузнецк (3843)20-46-81  
 Новосибирск (383)227-86-73  
 Омск (3812)21-46-40  
 Орел (4862)44-53-42  
 Оренбург (3532)37-68-04  
 Пенза (8412)22-31-16  
 Россия (495)268-04-70

Пермь (342)205-81-47  
 Ростов-на-Дону (863)308-18-15  
 Рязань (4912)46-61-64  
 Самара (846)206-03-16  
 Санкт-Петербург (812)309-46-40  
 Саратов (845)249-38-78  
 Севастополь (8692)22-31-93  
 Симферополь (3652)67-13-56  
 Смоленск (4812)29-41-54  
 Сочи (862)225-72-31  
 Ставрополь (8652)20-65-13  
 Казахстан (772)734-952-31

Сургут (3462)77-98-35  
 Тверь (4822)63-31-35  
 Томск (3822)98-41-53  
 Тула (4872)74-02-29  
 Тюмень (3452)66-21-18  
 Ульяновск (8422)24-23-59  
 Уфа (347)229-48-12  
 Хабаровск (4212)92-98-04  
 Челябинск (351)202-03-61  
 Череповец (8202)49-02-64  
 Ярославль (4852)69-52-93

**Electrical parameters - continued**

Reactive energy	±0.05% (0.2A-120A), ±0.1% (0.001A-0.2A)
Apparent energy	±0.05% (0.2A-120A), ±0.1% (0.001A-0.2A)
Range	0°-360°
Error	±0.005°
Display range	0.0001°-359.99°
Range	45-65Hz
Display range	45.0000-65.0000
High frequency output(CH)	12000Hz
Low frequency output(CL)	5000Hz
Pulse ratio	1:1
Output level	5V
Input level	5V
Input frequency	Max. 1MHz

**Mechanical parameters**

Dimensions (W×H×D) (mm)	480×138×486
Weight (kg)	10

**Environmental conditions**

Ambient temperature	-10 °C to 45 °C
Influence of external fields	≤ 0.05 % / mT
Relative humidity	10%-80%

**Архангельск** (8182)63-90-72  
**Астана** (7172)727-132  
**Астрахань** (8512)99-46-04  
**Барнаул** (3852)73-04-60  
**Белгород** (4722)40-23-64  
**Брянск** (4832)59-03-52  
**Владивосток** (423)249-28-31  
**Волгоград** (844)278-03-48  
**Вологда** (8172)26-41-59  
**Воронеж** (473)204-51-73  
**Екатеринбург** (343)384-55-89  
**Иваново** (4932)77-34-06

**Ижевск** (3412)26-03-58  
**Иркутск** (395)279-98-46  
**Казань** (843)206-01-48  
**Калининград** (4012)72-03-81  
**Калуга** (4842)92-23-67  
**Кемерово** (3842)65-04-62  
**Киров** (8332)68-02-04  
**Краснодар** (861)203-40-90  
**Красноярск** (391)204-63-61  
**Курск** (4712)77-13-04  
**Липецк** (4742)52-20-81  
**Киргизия** (996)312-96-26-47

**Магнитогорск** (3519)55-03-13  
**Москва** (495)268-04-70  
**Мурманск** (8152)59-64-93  
**Набережные Челны** (8552)20-53-41  
**Нижний Новгород** (831)429-08-12  
**Новокузнецк** (3843)20-46-81  
**Новосибирск** (383)227-86-73  
**Омск** (3812)21-46-40  
**Орел** (4862)44-53-42  
**Оренбург** (3532)37-68-04  
**Пенза** (8412)22-31-16  
**Россия** (495)268-04-70

**Пермь** (342)205-81-47  
**Ростов-на-Дону** (863)308-18-15  
**Рязань** (4912)46-61-64  
**Самара** (846)206-03-16  
**Санкт-Петербург** (812)309-46-40  
**Саратов** (845)249-38-78  
**Севастополь** (8692)22-31-93  
**Симферополь** (3652)67-13-56  
**Смоленск** (4812)29-41-54  
**Сочи** (862)225-72-31  
**Ставрополь** (8652)20-65-13  
**Казахстан** (772)734-952-31

**Сургут** (3462)77-98-35  
**Тверь** (4822)63-31-35  
**Томск** (3822)98-41-53  
**Тула** (4872)74-02-29  
**Тюмень** (3452)66-21-18  
**Ульяновск** (8422)24-23-59  
**Уфа** (347)229-48-12  
**Хабаровск** (4212)92-98-04  
**Челябинск** (351)202-03-61  
**Череповец** (8202)49-02-64  
**Ярославль** (4852)69-52-93