

# GF312B2

## Portable Three Phase Standard Meter

*GF312B2 portable three phase standard reference meter high accuracy 0.02%. It can be applied in following area:*

*Electric power department*

*Measuring and quality examining department*

*Electrical lab*

### Features

1. High accuracy up to 0.02%
2. Metal body, strong and reliable
3. DSP+32 bit ARM technology
4. Measurement 2~51 times harmonics
5. Waveform display function
6. Vector diagram function
7. Energy accumulating function
8. 7 inch TFT color LCD
9. Suit for testing in the field or in the lab



### Parameters

Electrical parameters	
Accuracy class	0.02% , 0.05%
Power supply	85-450V, 50/60Hz±2Hz
Power consumption	13VA
Communication port	RS232 , USB
Test Voltage	
Range	30-560V
Error	±0.02% (30V-560V) ±0.05% (5V-30V)
Harmonic	2 <sup>nd</sup> -51 <sup>st</sup>
Test Current	
Range (direct connection)	20mA-120A
Error (direct connection)	±0.02% (100mA-120A) ±0.05% (20mA-100mA)
Harmonic	2 <sup>nd</sup> -51 <sup>st</sup>

Архангельск (8182)63-90-72  
 Астана (7172)727-132  
 Астрахань (8512)99-46-04  
 Барнаул (3852)73-04-60  
 Белгород (4722)40-23-64  
 Брянск (4832)59-03-52  
 Владивосток (423)249-28-31  
 Волгоград (844)278-03-48  
 Вологда (8172)26-41-59  
 Воронеж (473)204-51-73  
 Екатеринбург (343)384-55-89  
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58  
 Иркутск (395)279-98-46  
 Казань (843)206-01-48  
 Калининград (4012)72-03-81  
 Калуга (4842)92-23-67  
 Кемерово (3842)65-04-62  
 Киров (8332)68-02-04  
 Краснодар (861)203-40-90  
 Красноярск (391)204-63-61  
 Курск (4712)77-13-04  
 Липецк (4742)52-20-81  
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13  
 Москва (495)268-04-70  
 Мурманск (8152)59-64-93  
 Набережные Челны (8552)20-53-41  
 Нижний Новгород (831)429-08-12  
 Новокузнецк (3843)20-46-81  
 Новосибирск (383)227-86-73  
 Омск (3812)21-46-40  
 Орел (4862)44-53-42  
 Оренбург (3532)37-68-04  
 Пенза (8412)22-31-16  
 Россия (495)268-04-70

Пермь (342)205-81-47  
 Ростов-на-Дону (863)308-18-15  
 Рязань (4912)46-61-64  
 Самара (846)206-03-16  
 Санкт-Петербург (812)309-46-40  
 Саратов (845)249-38-78  
 Севастополь (8692)22-31-93  
 Симферополь (3652)67-13-56  
 Смоленск (4812)29-41-54  
 Сочи (862)225-72-31  
 Ставрополь (8652)20-65-13  
 Казахстан (772)734-952-31

Сургут (3462)77-98-35  
 Тверь (4822)63-31-35  
 Томск (3822)98-41-53  
 Тула (4872)74-02-29  
 Тюмень (3452)66-21-18  
 Ульяновск (8422)24-23-59  
 Уфа (347)229-48-12  
 Хабаровск (4212)92-98-04  
 Челябинск (351)202-03-61  
 Череповец (8202)49-02-64  
 Ярославль (4852)69-52-93

**Electrical parameters - continued**
**Power measure error**

Active power (direct connection)	±0.02% (0.1A-120A) ±0.05% (0.02A-0.1A)
Reactive power (direct connection)	±0.05% (0.1A-120A)

**Energy measure error**

Active energy (direct connection)	±0.02% (0.1A-120A) ±0.05% (0.02A-0.1A)
Reactive energy (direct connection)	±0.05% (0.1A-120A)

**Phase angle**

Range	0° ~ 360°
Error	±0.02°

**Frequency**

Range	45-65Hz
-------	---------

**Pulse output**

Energy constant	1-250000
Pulse ratio	1:1
Output level	5V

**Pulse input**

Input channel	1
Input level	5-24V
Input frequency	Max. 2MHz

**Display**

Resolution	7"STN (800×480)
------------	-----------------

**Mechanical parameters**

Dimensions (W×H×D) (mm)	365×269×151
Weight (kg)	4

**Environmental conditions**

Ambient temperature	-10°C to 40°C
Relative humidity	30%-80%

**Архангельск** (8182)63-90-72  
**Астана** (7172)727-132  
**Астрахань** (8512)99-46-04  
**Барнаул** (3852)73-04-60  
**Белгород** (4722)40-23-64  
**Брянск** (4832)59-03-52  
**Владивосток** (423)249-28-31  
**Волгоград** (844)278-03-48  
**Вологда** (8172)26-41-59  
**Воронеж** (473)204-51-73  
**Екатеринбург** (343)384-55-89  
**Иваново** (4932)77-34-06

**Ижевск** (3412)26-03-58  
**Иркутск** (395)279-98-46  
**Казань** (843)206-01-48  
**Калининград** (4012)72-03-81  
**Калуга** (4842)92-23-67  
**Кемерово** (3842)65-04-62  
**Киров** (8332)68-02-04  
**Краснодар** (861)203-40-90  
**Красноярск** (391)204-63-61  
**Курск** (4712)77-13-04  
**Липецк** (4742)52-20-81

Киргизия (996)312-96-26-47

**Магнитогорск** (3519)55-03-13  
**Москва** (495)268-04-70  
**Мурманск** (8152)59-64-93  
**Набережные Челны** (8552)20-53-41  
**Нижний Новгород** (831)429-08-12  
**Новокузнецк** (3843)20-46-81  
**Новосибирск** (383)227-86-73  
**Омск** (3812)21-46-40  
**Орел** (4862)44-53-42  
**Оренбург** (3532)37-68-04  
**Пенза** (8412)22-31-16

Россия (495)268-04-70

**Пермь** (342)205-81-47  
**Ростов-на-Дону** (863)308-18-15  
**Рязань** (4912)46-61-64  
**Самара** (846)206-03-16  
**Санкт-Петербург** (812)309-46-40  
**Саратов** (845)249-38-78  
**Севастополь** (8692)22-31-93  
**Симферополь** (3652)67-13-56  
**Смоленск** (4812)29-41-54  
**Сочи** (862)225-72-31  
**Ставрополь** (8652)20-65-13

Казахстан (772)734-952-31

**Сургут** (3462)77-98-35  
**Тверь** (4822)63-31-35  
**Томск** (3822)98-41-53  
**Тула** (4872)74-02-29  
**Тюмень** (3452)66-21-18  
**Ульяновск** (8422)24-23-59  
**Уфа** (347)229-48-12  
**Хабаровск** (4212)92-98-04  
**Челябинск** (351)202-03-61  
**Череповец** (8202)49-02-64  
**Ярославль** (4852)69-52-93