

T-209

Circuit Breaker Tester/Circuit Breaker Analyzer

T-209 Circuit Breaker Tester can test the vacuum circuit breaker, SF₆, oil circuit breaker, GIS and etc. the test parameters include, close or open time, delta time, bounce time, bounce cycles, multi-operation, stroke, gap, over-travel, overshoot, rebound and the speed, with the ability of test results and graph display.



Features

1. Immunity : withstand the 550KV electrostatic environment
2. Transducer: with one analog transducer test ability .
3. Standard : with the standard of DL/T846.3—2004 (P.R.C.)
4. Power: with internal dc power ,the voltage ranges from 15v to 250v.
5. Trigger: with four triggers to start the recording ,channels state, voltage, current and transducer.
6. HMI: via keypad and a large transflective LCD display (320 x 240 pixels).
7. Speed: supply series of speed definition with editable and un-editable selection.
8. Recording: with twelve channels ,coil current and transducer .
9. Print: with internal installed 58mm wide thermal printer.
10. Comunication: with RS232 and USB communication interface.
11. Memory: with a SD card of 2GB,the maximum storage ability is 100 test results.
12. USB FLASH: USB and RS232 interface for data communication with the PC.
13. Help : the instrument has internal help topic .

Parameters

Electrical parameters		
Power supply		Single phase AC 220V±10% or 110V±10%, 50/60HzAC
Immunity		withstand the 550KV electrostatic environment
Test channels		12 channels with 25V, the current is 50mA
Transducer		one analog transducer
TIME	Recording time length	0~9.9s
	Time accuracy	±0.1%reading ± 2 LSB
	Resolution	0.1ms

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Electrical parameters - continued

Motion	Ranges	0~1000mm
	Accuracy	±1% reading ±1LSB
	Resolution	0.1mm
Velocity	Ranges	0~20.00m/s
	Accuracy	±1%reading ±1LSB
	Resolution	0.01m/s
DC POWER	Ranges	15~260V
	Max current	20A
	Accuracy	±1%reading ±1LSB
	Load change	≤1%
TRIGGER	Voltage	15~260V
	Current	0.1-20A
	Transducer	the transducer states changes
	Channels	channels states changed
Memory	SD card of 2GB, the maximum storage ability is 100 test results	
LCD	5.7"black and white LCD display (320 x 240 pixels)	
Communication	RS232 and USB communication interface	
Printer	internal installed 58mm wide thermal printer.	
Standard	DL/T846.3-2004, IEC61010-1, IEC61326-1	

Mechanical parameters

Dimension (L×W×H) (mm)	380x262x120
Weight (kg)	6

Environmental conditions

Operating temperature	-10°C to 50°C
Storage temperature	-20°C to 70°C
Relative humidity	≤95%RH

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93