

GF8002

BeiDou/GPS Time Server

GF8002 BeiDou / GPS time server is developed by our company based on GPS timing technology device. It can display and send standard time. The time server uses the PPS and time message of BeiDou Navigation System and GPS (Global Positioning System) satellite to output time synchronization pulse. The device uses SMT surface mount technology for production and high-speed chip for control, with high precision, high stability, strong function, no accumulative error, cost-effective and easy to operate. It is also not limited by geographical and climatic conditions. The device can be widely used in electric power system, network synchronization, communication, traffic management and national defense need timing and punctuality etc.



The device has a variety of interfaces. such as RJ45, RS-232, RS-422/RS-485, IRIG-B, TTL Pulse etc. Multi-channel output pulses such as seconds, minutes and hours (free translation), convenient connections and related device, implements unidirectional or bi-directional communication.

Applications

1. Electric power system
2. Power plant
3. Network time synchronization
4. Mobile communication system
5. Traffic management system
6. Airport time system
7. Hospital time system

Features

1. Optional GPS or BeiDou or CDMA three satellite receiving modes, high signal strength, local distributed installation is convenient. Especially suitable for communication base station, power plant, substation, machine room and other equipment time synchronization.
2. All-weather signal coverage to ensure long-term continuous high-reliability high-precision timing.
3. The 32-bit high-speed microprocessor + large-scale integrated FPGA chip, parallel high-speed data processing and various codes, excellent performance.
4. High-precision punctuality frequency is derived from adaptive synchronization technology, closed-loop control

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

punctuality technology to tame constant temperature crystal oscillator, to achieve long-time high-precision punctuality.

5. Satellite signal receiving and self-service hot standby, according to priority automatically select clock source, seamless switching.
6. Separate 10 M/100M network ports (each port has a separate MAC address), flexible configuration, can be used in different sub-nets or different physical isolation networks, using NTP/SNTP protocols to provide time synchronization services.
7. Provide programmable TTL pulse, can be set to PPS, PPM and PPH, flexible and convenient.
8. High performance, wide range switching power supply, AC-DC compatible input, convenient and reliable, stable operation.
9. All signal input and output interfaces are photoelectric isolation measures, safe and reliable.
10. 1 U Frame structure ,19 inch standard chassis, easy installation and maintenance.
11. Central master clock has 1 channel pulse ,10 channels B code ,3 channels 232 serial port ,3 channels 485 serial port ,2 channels Ethernet.

Parameters

Parameters					
1. Output Signal					
Timing signal type	Interface Type	Timing accuracy		Interface parameters	Number of interfaces
		Beidou-1	GPS		
Pulse	5V TTL level	-0.14 μ S	μ S 0.06	Phoenix terminal	1 channel
IRIG-B Time Code	RS485 level	μ S 0.12	μ S 0.2	Phoenix terminal	10 channels
Serial port	RS232	mS 0.18	mS 0.18	RJ45 interface	3 channels
	RS485/422	mS 0.18	mS 0.18	RJ45 interface	3 channels
Ethernet	NTP/SNTP	mS 10	mS 10	RJ45 interface	2 channels
2. Input Signal					
Name of clock source	Technical parameters				Remarks
Beidou-1	Receiver frequency :1561 MHz (B1 signal)				Optional
	Acceptance sensitivity :-127.6 dBmW				
	Capture time :35 S < 10 S; hot start and cold start				
	Timing accuracy : \leq 100 ns(unidirectional), \leq 20 ns(bidirectional)				
GPS	Receiver frequency :1575.42 MHz (L1 signal)				Optional
	Receiving sensitivity: capture <-160 dBW, tracking <-163 dBW				
	Capture time :200 S <25 S; hot start and cold start				
	Timing accuracy : \leq 100 ns (1pps versus UTC time)				
	Simultaneous tracking: no less than 4 satellites in cold start; no less than 1 satellite in hot start; up to 12 satellites can be tracked at the same time, parallel 12 channels.				

Core punctuality clock module	Adopt high precision constant temperature crystal frequency precision reaches 2 E-11 order of magnitude.	Built-in
	Self-service error $\leq 18 \mu s/24H$.	

3.Others

Name of parameter	Parameters
Environmental parameters	Working temperature :-20 to +70oC
	Storage temperature :-45 to +85oC
	Humidity :<95%
Power supply	Power supply :220 V \pm 20% or 110 V \pm 20%,47 Hz-63 Hz
	DC power supply :220 V \pm 20% or 110 V \pm 20%
	Power consumption $\leq 10 W$
EMC grade	Grade IV specified in the GB/T 17626-2008
Alarm signal	Relay air contact (250 V,5A)
Appearance Weight	Standard 19" Chassis , hight is 1U, Integrated structure , weight is 2 KG.

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://gfuve.nt-rt.ru/> || gfv@nt-rt.ru