

# GF2015

## Primary Current Recorder

1. *Collect and analyze load profiles*
2. *Easily clamps to the line in seconds*
3. *Check for load balance*
4. *Patented open CT sensor with  $\pm 1\%$  accuracy*
5. *433M communication with no annoying cables to connect*
6. *Recorded data quickly downloads into the user's PC*
7. *PC-LinkSoftware interface downloads directly into Microsoft Excel*
8. *Generate reports and create graphs for profile analysis*



## Features

1. The Primary current recorder uses the same sensor technology as the original Rogowski Coil. The True RMS inductive sensor does not use magnetic materials. The opening of the sensor is electronically closed and external currents are electronically rejected.
2. The accuracy, external current reject, and range of currents measured by the patented amp sensor substantially exceed the performance of the best clamp-on sensors. The key feature of the unit is the ability to leave it deployed on the line to record readings every 15 minutes for 90+ days. It easily attaches to the line with a standard insulating bar. Once on the line, it immediately begins to collect and record the primary current on the line.
3. The Primary current recorder is equipped with a 433M wireless port for communicating the recorded data into the user's PC. The data is downloaded through GF2015S PC-LinkSoftware software, which allows the user to download, view and query the data stored on the Primary current recorder.
4. The housing of the Primary current recorder is made of ABS+PC and is built to operate safely, even in severe utility environments. It is resistant to shock, repels water and is unsusceptible to flame. It also operates within a wide temperature range. The Primary current recorder has the screw insulation bar of installation, which allows it to hang on the line securely in all weather conditions.
5. PC-LinkSoftware is a user-friendly software interface that allows the user to download, view, graph and export data from the Primary current recorder into Microsoft Excel. The data directly transfers from the Primary current recorder into Excel through an 433M Port.



Архангельск (8182)63-90-72  
Астана (7172)727-132  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89  
Иваново (4932)77-34-06

Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Новокузнецк (3843)20-46-81  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16

Пермь (342)205-81-47  
Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Симферополь (3652)67-13-56  
Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35  
Тверь (4822)63-31-35  
Томск (3822)98-41-53  
Тула (4872)74-02-29  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

## Parameters

### Basic parameters

Recording ammeter kit	3 wireless current sensors (GF2015A, GF2015B, GF2015C) 433 HHT(handheld terminal) or 433M wireless data reader(GF2015R) PC-LinkSoftware software(GF2015S) Carrying case
Data recording interval	5min, 10min,15min, 30min; Interval user settable from 1-60min
Communication distance(wireless)	100m
Communication	433M, 868M or 915M (option)
Installation	Installation with electricity; Disassemble with electricity
Battery	3.6 volt lithium battery,19000mAh; Battery can be replaced
Software requirements	PC-Linksoftware & microsoft Excel
Processor	100 MHz or higher ( 200 MHz or higher recommended)
RAM	32 MB, 64M recommended
Drive space	15 MB to load software, 10 MB of operating Space
Use of position	Outdoor or indoor

### Electrical parameters

#### Range of operation

Voltage	69kV,35kV,20KV, 10kV, 6kV
Current	1 to 100A, 1 to 300A, 1 to 600A, 1 to 1000A, 1 to 2000A
Sensor opening	Up to 2.5 cm

#### Resolution

1 to 99.9A	0.1A
100 to 2000A	1A
Amps accuracy	±1% of reading plus 2 counts
Frequency	60Hz (57-63 Hz) or 50Hz (47-53 Hz) models available

### Mechanical parameters

Dimensions (WxDxH) (cm)	18x9.5x4.62
Weight (kg)	0.58

### Environmental conditions

Operating temp.	-40°C to 60°C
-----------------	---------------

**Архангельск** (8182)63-90-72  
**Астана** (7172)727-132  
**Астрахань** (8512)99-46-04  
**Барнаул** (3852)73-04-60  
**Белгород** (4722)40-23-64  
**Брянск** (4832)59-03-52  
**Владивосток** (423)249-28-31  
**Волгоград** (844)278-03-48  
**Вологда** (8172)26-41-59  
**Воронеж** (473)204-51-73  
**Екатеринбург** (343)384-55-89  
**Иваново** (4932)77-34-06

**Ижевск** (3412)26-03-58  
**Иркутск** (395)279-98-46  
**Казань** (843)206-01-48  
**Калининград** (4012)72-03-81  
**Калуга** (4842)92-23-67  
**Кемерово** (3842)65-04-62  
**Киров** (8332)68-02-04  
**Краснодар** (861)203-40-90  
**Красноярск** (391)204-63-61  
**Курск** (4712)77-13-04  
**Липецк** (4742)52-20-81

**Магнитогорск** (3519)55-03-13  
**Москва** (495)268-04-70  
**Мурманск** (8152)59-64-93  
**Набережные Челны** (8552)20-53-41  
**Нижний Новгород** (831)429-08-12  
**Новокузнецк** (3843)20-46-81  
**Новосибирск** (383)227-86-73  
**Омск** (3812)21-46-40  
**Орел** (4862)44-53-42  
**Оренбург** (3532)37-68-04  
**Пенза** (8412)22-31-16

**Пермь** (342)205-81-47  
**Ростов-на-Дону** (863)308-18-15  
**Рязань** (4912)46-61-64  
**Самара** (846)206-03-16  
**Санкт-Петербург** (812)309-46-40  
**Саратов** (845)249-38-78  
**Севастополь** (8692)22-31-93  
**Симферополь** (3652)67-13-56  
**Смоленск** (4812)29-41-54  
**Сочи** (862)225-72-31  
**Ставрополь** (8652)20-65-13

**Сургут** (3462)77-98-35  
**Тверь** (4822)63-31-35  
**Томск** (3822)98-41-53  
**Тула** (4872)74-02-29  
**Тюмень** (3452)66-21-18  
**Ульяновск** (8422)24-23-59  
**Уфа** (347)229-48-12  
**Хабаровск** (4212)92-98-04  
**Челябинск** (351)202-03-61  
**Череповец** (8202)49-02-64  
**Ярославль** (4852)69-52-93

**Киргизия** (996)312-96-26-47

**Россия** (495)268-04-70

**Казахстан** (772)734-952-31