

GF2011

WIRELESS HIGH VOLTAGE AMMETER

GF2011 High Voltage Ammeter specially designed and manufactured for High voltage AC current measurement, low voltage AC current, current leakage measurement, online AC current measurement. It consists of special high voltage detector, wireless receiver and high voltage insulation rod.

Apply to power plant, substation, industrial and mining enterprise, inspection station, electrician maintenance department for current sensing and field working.



Features

1. Adopt latest CT technology and integrated mask digital technology
2. Wireless transmission distance 30m, can transmit through building barriers
3. Integrated design ensures uninterrupted year-round high precision, high reliability and high stability test
4. Have peak value maintaining, data maintaining, data memory function
5. Easy to install and remove with power on
6. Insulation rod has the characteristics of moisture resistance, high temperature resistance, impact resistance, bending resistance, high insulation and scalability
7. Can accurately measure 0.00mA-1200A current or leakage current
8. Can test high and low voltage changing ratio, respectively test the first loop and secondary loop high and low voltage current, and then obtain the voltage change through manually calculation

Parameters

Electrical parameters	
Power supply	Ammeter: DC6V Alkaline Dry Battery (1.5V AAA X 4), Receiver: DC7.5V Alkaline Dry Battery (1.5V AA X 5), working 10 hours
Test mode	Clamp CT, integral approach
Transmission mode	Wireless transmission, the maximum distance of straight line transmission is about 30m
Display mode	4 bit LCD display, with backlight function
Sampling rate	2 times/second
Measurement scope	0.00mA-1200A (50/60Hz automatic)

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

Electrical parameters-continued

Resolution	0.01mA
Shift	0.00mA-1200A automatic shift
Accuracy (23°C±5°C, below 70%RH)	0.000mA-120.00A: ±1%±3dgt 120.00A-1200.0A: ±1%±5dgt
Line voltage	Below 69KV line test (with 5 insulation rods operation)
Data memory	99 sets
Automatic shutdown	15 minutes after boot
Battery voltage	<4.8V alarm active
Insulation strength	AC 100kV/rms (between the 5 th insulation rod and high voltage Ammeter core)
Structure	Anti-drip type II
Safety provisions	IEC1010-1, IEC1010-2-032, Pollution Class 2, CAT III (600V), IEC61326(EMC standard)

Mechanical parameters

LCD dimensions (mm)	47×28.5
Meter dimension (LxWxH) (mm)	87×262×37
Meter weight	2.5kg (including insulation rod and battery, tester 335g)
Clamp dimension (mm)	Φ50
Insulation rod dimension	Φ50mm, 1m/piece (5m)

Environmental conditions

Working temperature	-25°C to 40°C
Working humidity	Below 80%Rh
Storage temperature	-10°C to 60°C
Storage humidity	Below 70%Rh

Accessories

Ammeter	1 pc
Receiver	1 pc
Ammeter box	1 pc
Telescopic insulation rod (5m)	1 pc
Battery	Rechargeable Alkaline Dry Battery(AA X 5+AAA X 4)

Model
Description

GF2011	Wireless
GF2011B	Base Display

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31